

DATASHEET



General data

The Digital Toslink/Optical SPDIF to RCA Audio Converter lets you convert a 2-channel Digital Coaxial or Toslink/Optical SPDIF input signal into an RCA and 3.5mm analog stereo output.

Perfect for home and professional audio applications, this SPDIF to RCA audio converter saves the cost of upgrading equipment for compatible connections, and offers separate Digital Coax and Toslink inputs for dual-function conversion. The small form factor design makes it suitable for installation into virtually any location, regardless of space constraints, while still providing a lossless audio signal. Plus, the digital coaxial or Toslink to RCA converter supports plug-and-play installation, saving you time and hassle.

Converts SPDIF Optical or Coaxial digital PCM audio input to analog stereo L/R RCA and 3.5mm Cable outputs simultaneously

Supported sample rates including 32 KHz 44.1 KHz, 48 KHz, 96 KHz and 192 KHz,

Support 24-bit S/PDIF incoming bit stream

Auto sensing input selection with priority given to SPDIF; disable / disconnect SPDIF input for coaxial Input application

Technical specifications

Input Audio: Coaxial or Toslink digital audio

Output Audio: L/R audio or 3.5 mm

Input Audio Connector: Toslink 1 x RCA (Coaxial)

Output Audio Connector: 2 x RCA (R/L) 3.5mm

Sampling Rate: 32, 44.1, 48 and 96 KHz

This datasheet was created automatically on 25-09-2026 . Technical changes reserved.



DATASHEET

Dimensions (L-W-H): 56 x 53 x 21 mm

Power Consumption: 0.5 watts (Max)

Powered by: USB power cable

Environmental information

Operating Temperature: from 0°C to +70°C

Operating Humidity: 10% to 85 % RH (no condensation)

Storage Temperature: from -10°C to +80°C

Storage Humidity: from 5% to 90 % RH (no condensation)

Package contents

Main Unit

USB Power Cable

User Manual

Tekniske egenskaber

Available variants

ArtNr.	Bezeichnung	Unique
IDATA-SPDIF-9		Unique

Note on Intended Use

This data sheet is intended solely to describe the technical characteristics of the product. It does not replace an assessment of the product's suitability for a specific application. The user is responsible for ensuring that the product is used in accordance with its technical specifications and applicable legal and regulatory requirements.

This datasheet was created automatically on 25-09-2026 . Technical changes reserved.

